

LIGHTING WER

Rite



Rite Lighting Tower – An

ideal solution to keep you ON

8m

Height

_

_



XX.

1400:Lamp 1400W -

- L: Lighting Tower
- 5: 50Hz -----
- T: Trailer -----



MULTI-PROTECTIONS



TRAILER SYSTEM



Road low-speed version, single-axle double-wheel, leaf spring suspension axle, with service brake, meeting the driving speed of 40km/h;

Optional road high-speed version, adjustable height traction head, mast lifting safety system;

STANDARD CONFIGURATION

- 1. 50°C radiator for tropical environments;
- 2. The radiator has an overflow pot to prevent the coolant from overflowing;
- The core of the radiator is equipped with a protective net, which can effectively prevent the heat sink from being damaged;
- 4. Mains floating charge to ensure the starting capacity of the starting battery at any time;
- 5. A negative switch and an isolation box to ensure the safety of battery power supply;
- Configure the main power supply, lighting, and output socket with ABB MCB, of which the main power switch is equipped with leakage protection;
- 7. Mains power input socket to meet the scene of directly using the mains power for lighting;
- The oil-water separator is equipped as standard, which can effectively prevent the cleanliness of the fuel from affecting the engine;
- The manual oil pump is equipped as standard, which is convenient for quick extraction of waste oil during maintenance;
- 10. A spirit level to facilitate leveling when the lighthouse is unfolded;
- 11. Exhaust manifold, supercharger with protective cover; exhaust pipe, muffler with heat insulation sleeve;
- Fuel tank with double-layer base, with a fireproof cap on the breathing port; the capacity meets the lighting requirement for 60 hours, not less than 100L; the site is designed to prevent leakage, which can accommodate leaked fuel, engine oil, and coolant;
- 13. Folder is installed on the observation door of the control cabinet;
- 14. Stainless steel hardware is used on light tower canopy;
- 15. Fuel port and emergency stop button outside the enclosure;
- 16. The sewage outlet is led out together and has drain plug;
- 17. With forklift positions and hoisting holes;

OPTIONAL

- 1. The air intake filter on the cabinet can be quickly disassembled, which can be used in a dusty environment;
- The number of output sockets can be customized according to the needs to meet the use of different power consumption;
- 3. Engine exhaust spark extinguishing device;
- 4. Water jacket heater;
- 5. The one-way valve of the engine fuel inlet line, and the auxiliary fuel electronic fuel pump;

LOADING

Satisfy two layers of stacked cabinets; the number of 20-foot cabinets is 6 units, and the number of 40-foot cabinets is 18 units.









enquiries@ritewat.uk



+447746176656



www.ritewat.uk

For more information about our products and services, please contact Ritewat UK Ltd